


# Exciters and Governors: Exciter DC2A



|  |   |
|--|---|
| Exciters and Governors: Exciter DC2A ..... | 1 |
| 1 Description.....                         | 1 |
| 1.1 Pins .....                             | 1 |
| 1.2 Parameters.....                        | 1 |
| 1.2.1 Data tab .....                       | 1 |
| 1.2.2 Exciter tab .....                    | 2 |
| 2 Initial conditions .....                 | 2 |
| 3 References .....                         | 2 |

Tshibain Tshibungu, Jean Mahseredjian, 8/1/2016 1:13 PM

## 1 Description

This device is an implementation of the IEEE type DC2A excitation system model. This device is implemented as described in [1]. Implementation details can be viewed by inspecting the subcircuit of this device.

### 1.1 Pins

This device has 8 pins:

| Pin name | Type   | Description  | Units |
|----------|--------|--|-------|
| VREF     | Input  | Reference voltage of the stator terminal voltage           | pu    |
| Efss     | Input  | Steady-state field voltage at $t = 0$ , for initialization | pu    |
| VC       | Input  | Terminal voltage of synchronous machine, transducer output | pu    |
| VS       | Input  | Power System Stabilizer signal                             | pu    |
| VT       | Input  | Terminal voltage of synchronous machine                    | pu    |
| VUEL     | Input  | Under Excitation Limiter signal                            | pu    |
| EFD      | Output | The field voltage signal                                   | pu    |
| VF       | Output | The excitation system stabilizer signal                    | pu    |

### 1.2 Parameters

The default set of parameters can be found in [1].

#### 1.2.1 Data tab

The parameters on the Data tab are:

1. **Gain  $K_A$** : voltage regulator gain
2. **Time constant  $T_A$** : voltage regulator time constant

3. **Maximum regulator output  $V_{Rmax}$** : Maximum regulator voltage output
4. **Minimum regulator output  $V_{Rmin}$** : Minimum regulator voltage output
5. **Time constant  $T_B$** : time constant of the lead-lag compensator
6. **Time constant  $T_C$** : time constant of the lead-lag compensator
7. **Damping filter gain  $K_F$** : excitation control system stabilizer gain
8. **Damping filter time constant  $T_F$** : excitation control system stabilizer time constant
9. Under Excitation Limiter option: see explanations below.

There are two possible selections for the Under Excitation Limiter option:

1. VUEL not available or added to the reference voltage: this option can be selected when the VUEL input signal is zero (not connected) or when it is connected and added to the reference voltage.
2. VUEL connected to the high value gate (HV gate)

## 1.2.2 Exciter tab

The exciter tab allows to input:

1. **Gain  $K_E$** : exciter gain
2. **Time constant  $T_E$** : exciter time constant
3. **Field voltage  $E_{FD1}$** : The field exciter voltage point which is near the exciter ceiling voltage
4. **Field voltage  $E_{FD2}$** : The field exciter voltage point which is near 75% of  $E_{FD1}$
5. **Saturation function output  $SE_{E_{FD1}}$** : The exciter saturation function value at  $E_{FD1}$
6. **Saturation function output  $SE_{E_{FD2}}$** : The exciter saturation function value at  $E_{FD2}$

The exciter saturation function is defined as

$$S_E = A_{EX} e^{B_{EX} E_{FD}} \quad (1)$$

which gives the approximation saturation for any  $E_{FD}$  (exciter output voltage). According to [2] (see pages 562 and 563), the coefficients  $A_{EX}$  and  $B_{EX}$  can be found from:

$$A_{EX} = \frac{S_{E_{FD2}}^4}{S_{E_{FD1}}^3} \quad (2)$$

$$B_{EX} = \frac{4}{E_{FD1}} \ln \left( \frac{S_{E_{FD1}}}{S_{E_{FD2}}} \right) \quad (3)$$

In the literature [2]  $E_{FD1} = E_{FD_{max}}$  and  $E_{FD2} = E_{FD_{0.75max}}$ .

## 2 Initial conditions

The reference voltage  $V_{REF}$  can be manually or automatically set by connecting or not connecting the input signal  $V_{REF}$ , respectively. When  $V_{REF}$  is not connected (the signal is zero), the reference voltage is internally found from the steady-state solution. When  $V_{REF}$  is connected, its initial value must match the per unit steady-state voltage of the stator terminal voltage, since otherwise the generator voltage will not start at the actual steady-state.

## 3 References

- [1] "IEEE Recommended Practice for Excitation System Models for Power System Models for Power System Stability Studies," IEEE Standard 421.5-2005.
- [2] P. M. Anderson and A. A. Fouad, "Power system control and stability", second edition, IEEE Press, Wile Interscience, 2003.